

## USB 8 Relay Output Board

**Product Code:**

AUSB8RELAY USB 8 RELAY OUTPUT BOARD


**Bus:** USB 2.0 / RS-232/422/485

**Description:** 8 relay output channels

8 DPDT-Relays - 2 x COM/NO/NC

Max switching current: 1A  
Max contact rating for relay: 220V AC / 150V DC

8 LED correspond to output ports activation status.



**Connection:**

Easy exchange by interchangeable screw-terminals

**Features:**

For direct DIN-Rail mounting  
Also as board without  
DIN Rail adapter available

High Speed 8051  $\mu$ C Core  
USB 2.0 Function Controller  
Support USB ID 0~14 SET  
Support RS-232/422/485 Communicate  
POWER from External DC+5V 3A



**Software/Driver:**

Windows-XP Vista will use HID-interface and sample for programming,  
Linux driver and sample for programming.

**Package includes the following items:**

USB 8RELAY Board  
USB cable  
Software and Manual CD

**Operating temperature range:** from 0 to 33C.  
**Relative humidity range:** from 0 to 90%.  
**Size:** 160 mm x 120 mm x 55 mm

## DECISION COMPUTER INTERNATIONAL CO., LTD.



4/F No. 31, Alley 4, Lane 36, Sec.5  
Ming-Shen East Road

Taipei, Taiwan, R.O.C.

**Phone No :** +886 2 2766-5753  
**Fax No :** +886 2 2766 5702, 2756 9591  
**E - Mail :** [decision@ms1.hinet.net](mailto:decision@ms1.hinet.net)  
[decision@decision.com.tw](mailto:decision@decision.com.tw)  
**URL :** [www.decision.com.tw](http://www.decision.com.tw)